9.9mm (0.39INCH) SINGLE DIGIT NUMERIC DISPLAY

Part Number: SC39-12GWA G

Green

Features

- 0.39 inch digit height.
- Low current operation.
- Excellent character appearance.
- Easy mounting on P.C. boards or sockets.
- Mechanically rugged.
- Standard : gray face, white segment.
- RoHS compliant.

Description

The Green source color devices are made with Gallium Phosphide Green Light Emitting Diode.

Package Dimensions& Internal Circuit Diagram



SPEC NO: DSAA8804

APPROVED: WYNEC

REV NO: V.15 CHECKED: Joe Lee DATE: APR/01/2011 DRAWN: J.Yu

PAGE: 1 OF 6 ERP: 1301000942

Selection Guide									
Part No.	Dice	Lens Type	lv (ucd) [1] @ 10mA		Description				
			Min.	Тур.					
SC39-12GWA	Green (GaP)	White Diffused	2200	6400	Common Cathode, Rt. Hand Decimal.				

Note:

1. Luminous intensity/ luminous Flux: +/-15%.

Electrical / Optical Characteristics at TA=25°C

Symbol	Parameter	Device	Тур.	Max.	Units	Test Conditions
λpeak	Peak Wavelength	Green	565		nm	IF=20mA
λD [1]	Dominant Wavelength	Green	568		nm	I⊧=20mA
Δλ1/2	Spectral Line Half-width	Green	30		nm	IF=20mA
С	Capacitance	Green	15		pF	VF=0V;f=1MHz
Vf [2]	Forward Voltage	Green	2.2	2.5	V	IF=20mA
lr	Reverse Current	Green		10	uA	VR=5V

Notes: 1.Wavelength: +/-1nm. 2. Forward Voltage: +/-0.1V.

Absolute Maximum Ratings at TA=25°C

Parameter	Green	Units	
Power dissipation	62.5	mW	
DC Forward Current	25	mA	
Peak Forward Current [1]	140	mA	
Reverse Voltage	5	V	
Operating / Storage Temperature	-40°C To +85°C		
Lead Solder Temperature[2]	260°C For 3-5 Seconds		

Notes: 1. 1/10 Duty Cycle, 0.1ms Pulse Width. 2. 2mm below package base.







Soldering General Notes:

- a. Through—hole displays are incompatible with reflow soldering.
- b. If components will undergo multiple soldering processes, or other processes where the components may be subjected to intense heat, please check with Kingbright for compatibility.

CLEANING

1.Mild "no-clean" fluxes are recommended for use in soldering.

2. If cleaning is required, Kingbright recommends to wash components with water only. Do not use harsh organic solvents for cleaning, because they may damage the plastic parts .And the devices should not be washed for more than one minute.

CIRCUIT DESIGN NOTES

 Protective current-limiting resistors may be necessary to operate the Displays.
LEDs mounted in parallel should each be placed in series with its own current-limiting resistor.

