


**Features:**

- Center amplifying gate
- Metal case with ceramic insulator
- Low on-state and switching losses

**Typical Applications**

- AC controllers
- DC and AC motor control
- Controlled rectifiers

$I_{T(AV)}$	<b>1240A</b>
$V_{DRM}/V_{RRM}$	<b>1900~3000V</b>
$I_{TSM}$	<b>20 kA</b>
$I^2t$	<b>2000 <math>10^3 A^2S</math></b>



SYMBOL	CHARACTERISTIC	TEST CONDITIONS	$T_j(^{\circ}C)$	VALUE			UNIT
				Min	Type	Max	
$I_{T(AV)}$	Mean on-state current	180° half sine wave 50Hz Double side cooled,  $T_c=55^{\circ}C$ $T_c=70^{\circ}C$  old model	125			1460	A
						1240	
						1000	
$V_{DRM}$ $V_{RRM}$	Repetitive peak off-state voltage Repetitive peak reverse voltage	$V_{DRM} \& V_{RRM}$ tp=10ms $V_{DSM} \& V_{RSM} = V_{DRM} \& V_{RRM} + 100V$	125	1900		3000	V
$I_{DRM}$ $I_{RRM}$	Repetitive peak current	$V_{DM}=V_{DRM}$ $V_{RM}=V_{RRM}$	125			80	mA
$I_{TSM}$	Surge on-state current	10ms half sine wave $V_R=0.6V_{RRM}$	125			20	kA
$I^2t$	$I^2T$ for fusing coordination					2000	$A^2s * 10^3$
$V_{TO}$	Threshold voltage		125			1.11	V
$r_T$	On-state slop resistance					0.36	$m\Omega$
$V_{TM}$	Peak on-state voltage	$I_{TM}=2550A, F=24kN$	125			2.02	V
$dv/dt$	Critical rate of rise of off-state voltage	$V_{DM}=0.67V_{DRM}$	125			1000	V/ $\mu$ s
$di/dt$	Critical rate of rise of on-state current	$V_{DM}=67\%V_{DRM}$ to 1500A, Gate pulse $t_r \leq 0.5\mu s$ $I_{GM}=1.5A$	125			150	A/ $\mu$ s
$Q_{rr}$	Recovery charge	$I_{TM}=2000A, tp=2000\mu s, di/dt=-20A/\mu s,$ $V_R=50V$	125		1600		$\mu C$
$I_{GT}$	Gate trigger current	$V_A=12V, I_A=1A$	25	40		300	mA
$V_{GT}$	Gate trigger voltage			0.8		3.0	V
$I_H$	Holding current			20		300	mA
$V_{GD}$	Non-trigger gate voltage	$V_{DM}=67\%V_{DRM}$	125	0.3			V
$R_{th(j-c)}$	Thermal resistance Junction to case	At 180° sine double side cooled Clamping force 24kN				0.020	$^{\circ}C / W$
$R_{th(c-h)}$	Thermal resistance case to heatsink					0.005	
$F_m$	Mounting force			19		26	kN
$T_{stg}$	Stored temperature			-40		140	$^{\circ}C$
$W_t$	Weight				440		g
Outline		KT50ct					




Fig.1




Fig.2




Fig.3




Fig.4




Fig.5




Fig.6




Fig.7




Fig.8




Fig.9




Fig.10

## Outline:

