


# 4PIN MINI-FLAT PHOTODARLINGTON PHOTOCOUPLER

#### Description

The KPC355NT series consist of a photodarlington optically coupled to a gallium arsenide infrared-emitting diodes in a 4-pin Mini-Flat package. The input-output isolation voltage is rated at 3750 Vrms.

#### Schematic



- 1. Anode
- 2. Cathode
- 3. Emitter
- 4. Collector

#### Features

- 1. Pb free and RoHS compliant
- 2. High current transfer ratio

(CTR: Min.600% at  $I_F = 1mA$ , Vce=2V)

3. High isolation voltage between input and output

(Viso: 3750Vrms)

- 4. Mini-flat package: compact 4 pin SOP with a 2.0mm profile
- 5. MSL class 1
- 6. Agency Approvals:
  - UL Approved (No. E169586): UL1577
  - c-UL Approved (No. E169586)
  - VDE Approved (No. 40014684): DIN EN 60747-5-5
  - FIMKO Approved EN62368-1, EN60601-1
  - CQC Approved: GB8898-2011, GB4943.1-2011


#### Applications


- System appliances, measuring instruments
- Industrial robots
- Copiers, automatic vending machines
- Signal transmission between circuits of different potentials and impedances
- Telephone sets
- Copiers, facsimiles
- Interface with various power supply circuits, power distribution boards
- Numerical control machines


# 4PIN MINI-FLAT PHOTODARLINGTON PHOTOCOUPLER

#### Outside Dimension

Unit: mm







TOLERANCE: ±0.2mm

### Device Marking



#### Notes:

Cosmo 355NT

YWW Y: Year code / WW: Week code

:CTR rank



# 4PIN MINI-FLAT PHOTODARLINGTON PHOTOCOUPLER

### Absolute Maximum Ratings

(Ta=25°℃)

	Parameter	Symbol	Rating	Unit
Input	Forward current	I <sub>F</sub>	50	mA
	Peak forward current	I <sub>FM</sub>	1	А
	Reverse voltage	V <sub>R</sub>	6	V
	Power dissipation	P <sub>D</sub>	70	mW
Output	Collector-Emitter voltage	V <sub>CEO</sub>	35	V
	Emitter-Collector voltage	V <sub>ECO</sub>	5	V
	Collector current	I <sub>C</sub>	150	mA
	Collector power dissipation	P <sub>C</sub>	150	mW
Total power dissipation		Ptot	170	mW
	Isolation voltage 1 minute	Viso	3750	Vrms
Operating temperature		Topr	-55 to +115	$^{\circ}\!\mathbb{C}$
Storage temperature		Tstg	-55 to +125	$^{\circ}\!\mathbb{C}$
Soldering temperature 10 seconds		Tsol	260	$^{\circ}\!\mathbb{C}$

### Electro-optical Characteristics

(Ta=25°C)

	Parameter	Symbol	Conditions	Min.	Тур.	Max.	Unit
Input	Forward voltage	V <sub>F</sub>	I <sub>F</sub> =20mA	-	1.2	1.4	V
	Peak forward voltage	$V_{FM}$	I <sub>FM</sub> =0.5A	-	-	3.5	V
	Reverse current	I <sub>R</sub>	V <sub>R</sub> =4V	-	-	10	uA
	Terminal capacitance	Ct	V=0, f=1KH <sub>Z</sub>	-	30	-	pF
Output	Collector dark current	I <sub>CEO</sub>	V <sub>CE</sub> =10V, I <sub>F</sub> =0	-	-	1.0	uA
Transfer charac- teristics	Current transfer ratio	CTR	I <sub>F</sub> =1mA, V <sub>CE</sub> =2V	600	1600	7500	%
	Collector-Emitter saturation	V <sub>CE</sub> (sat)	I <sub>F</sub> =20mA, Ic=1mA	-	-	1.0	V
	Isolation resistance	Riso	DC500V	5x10 <sup>10</sup>	-	-	Ω
	Floating capacitance	Cf	V=0, f=1MH <sub>Z</sub>	_	0.6	1.0	pF
	Cut-off frequency	fc	Vcc=5V,lc=2mA,R <sub>L</sub> =100 $\Omega$	-	7	-	kHz
	Response time (Rise)	tr	-Vce=2V,Ic=2mA,R <sub>L</sub> =100Ω	-	60	300	us
	Response time (Fall)	tf		-	53	250	us



# 4PIN MINI-FLAT PHOTODARLINGTON PHOTOCOUPLER


# Fig.1 Current Transfer Ratio vs. Forward Current

Classification table of current transfer ratio is shown below.

CTR RANK	CTR (%)
KPC355NT0E	Min.600


Ontent Language Management of the Language Manag

Fig.2 Collector Power Dissipation vs. Ambient Temperature




Ambient Temperature Ta (°C)

Fig.3 Collector Dark Current vs. Ambient Temperature




Ambient Temperature Ta (°C)

Fig.4 Forward Current vs. Ambient Temperature



Ambient Temperature Ta (°C)

Fig.5 Forward Current vs. Forward Voltage



Forward Voltage V<sub>F</sub> (V)

http://www.cosmo-ic.com



# 4PIN MINI-FLAT PHOTODARLINGTON PHOTOCOUPLER

# Fig.6 Collector Current vs. Collector-Emitter Voltage




Fig.8 Collector-Emitter Saturation Voltage vs. Forward Current




Fig.7 Relative Current Transfer Ratio vs. Ambient Temperature






Fig.9 Response Time vs. Load Resistance





# 4PIN MINI-FLAT PHOTODARLINGTON PHOTOCOUPLER

### Test Circuit for Response Time





### 4PIN MINI-FLAT PHOTODARLINGTON PHOTOCOUPLER

#### Recommended Soldering Conditions

(a) Infrared reflow soldering:

■ Peak reflow soldering : 260°C or below (package surface temperature)

■ Time of peak reflow temperature : 10 sec
■ Time of temperature higher than 230°C : 30-60 sec
■ Time to preheat temperature from 180~190°C : 60-120 sec


■ Time(s) of reflow: Two

■ Flux : Rosin flux containing small amount of chlorine (The

flux with a maximum chlorine content of 0.2 Wt% is

recommended.)

#### Recommended Temperature Profile of Infrared Reflow



#### (b) Wave soldering:

■ Temperature : 260°C or below (molten solder temperature)

■ Time : 10 seconds or less

■ Preheating conditions : 120°C or below (package surface temperature)

■ Time(s) of reflow : One

■ Flux: Rosin flux containing small amount of chlorine (The flux with a maximum

chlorine content of 0.2 Wt% is recommended.)

(c) Cautions:

■ Fluxes : Avoid removing the residual flux with freon-based and chlorine-based

cleaning solvent.

Avoid shorting between portion of frame and leads.



# 4PIN MINI-FLAT PHOTODARLINGTON PHOTOCOUPLER

### Numbering System

### **KPC355NT <u>Y</u> (Z)**

#### Notes:


KPC355NT = Part No.


Y = CTR rank (E)

Z = Tape and reel option (TLD  $\cdot$  TRU)

Option	Description	Packing quantity		
(TLD)	TLD tape & reel option	3000 units per reel		
(TRU)	TRU tape & reel option	3000 units per reel		

### • Recommended Pad Layout for Surface Mount Lead Form






Unit: mm

# 4PIN MINI-FLAT PHOTODARLINGTON PHOTOCOUPLER

### 4-pin Mini-Flat Carrier Tape & Reel



# cosmo

### **KPC355NT Series**

4PIN MINI-FLAT PHOTODARLINGTON PHOTOCOUPLER

#### Application Notice

The statements regarding the suitability of products for certain types of applications are based on cosmo's knowledge of general applications of cosmo products. Such statements are not binding statements about the suitability of products for a particular application. It is the customer's responsibility to verify the specifications are suitable for use in a particular application. Customers are solely responsible for all aspects of their own product design or applications. The parameters provided in the datasheet may vary in different applications and performance may vary over time. All operating parameters (including typical parameters) must be validated by customer's technical experts for different applications. cosmo assumes no liability for customer' product design or applications. Product specifications do not expand or otherwise change cosmo's terms and conditions of purchase, including but not limited to the warranty expressed therein.

When using cosmo products, please comply with safety standards and instructions. cosmo has no liability and responsibility to the damage caused by improper use of the instructions specified in the specifications.

cosmo products are designed for use in general electronic equipment such as telecommunications, office automation equipments, personal computers, test and measurement equipments, consumer electronics, industrial control, instrumentation, audio, video.

cosmo devices shall not be used in equipment that requires higher level of reliability and safety, such as nuclear power control equipment, telecommunication equipment(trunk lines), space application, medical and other life supporting equipments, and equipment for aircraft, military, automotive or any other application that can cause human injury or death.

cosmo reserves the right to change the specifications, data, characteristics, structure, materials and other contents at any time without notice. Please contact cosmo to obtain the latest specification.

cosmo disclaim any and all liability for any errors, inaccuracies or incompleteness contained in any datasheet or in any other disclosure relating to any product.