# HF161F-W

## SOLAR RELAY



CONTACT DATA

Contact gap	1.5mm -		
Contact arrangement		1A	
Contact resistance <sup>1)</sup>	100mΩ max.(at 1A 6VDC)		
Contact material	AgSnO <sub>2</sub>		
Contact rating	Resistive: 26A 250VAC Inductive: 31A 250VAC (cosø=0.8) 0.1s:10s		
Max. switching voltage		277VAC	
Max. switching current	31A 3		
Max. switching power	7750VA	8250VA	
Mechanical endurance	1 x 10 <sup>6</sup> 0PS	1 x 10⁵ops	
Electrical endurance	HT type: 3 x 10 <sup>4</sup> oPs (26A 250VAC, Resistive load, at 75℃, 1.5s on 1.5s off)		
Notes: 1)The data shown above are initial values.			

**CHARACTERISTICS** 

Insulation resistance		1000MΩ (at 500VDC)		
Dielectric strength	Between coil & contacts	4500VAC 1min		
	Between open contacts	2500VAC 1min		
Surge voltage (between coil & contacts)		10kV (1.2/50µs		
Operate time (at nomi. volt.)		20ms max.		
Release time (at nomi. volt.)		10ms max.		
Temperature rise		95K max. (Contact load current 31A, rated voltage excitation, at 60°C)		
(at nomi.	volt.)	70K max. (Contact load current 31A,		
		80% of rated voltage excitation, at 85°C)		
Shock	Functional	196m/s <sup>2</sup>		
resistance	Destructive	980m/s²		
Vibration resistance		10Hz to 55Hz 1.5mm DA		
Ambient temperature		-40°C to 85°C (Apply holding voltage to coil, which is 45% to 80% that of rated voltage)		
Humidity		5% to 85% RH		
Termination		PCB		
Unit weight		Approx. 21g		
Construction		Flux proofed		

Notes: The data shown above are initial values.

HONGFA RELAY ISO9001、ISO/TS16949、ISO14001、OHSAS18001、IECQ QC 080000 CERTIFIED

Features

- 31A switching capacity
- Applicable to inverter used for photovoltaic power generation systems
- Ideal for UPS
- 1.5mm contact gap (compliant to European Photovoltaic Standard VDE0126)
- 1.8mm contact gap (compliant to IEC 62109-2-2011)
- The clearance distance between contact and coil is bigger than 6.4mm, the creepage distance is bigger than 8mm. (special code 477:7.5mm)
- Low coil holding voltage contributes to saving energy of equipment.
- UL insulation system: Class F
- Environmental friendly product (RoHS compliant)
- Outline Dimensions:30.4mm x 15.9mm x 23.3mm

#### COIL

Coil power	Approx. 1.4W		
Holding voltage	35% to 120%UN (at 23°C)		
	45% to 80%Uℕ (at 85°C)		

Notes: 1)The coil holding voltage is the voltage of coil after being applied rated voltage for 100ms

2)The relay col does not allow applied more than maximum of holding voltage values for a long time (Eg: 120% Un at 23°C; 80% Un at 85°C), prevent overheating burned.

COIL DATA at 23°C				
Nominal Voltage VDC	Pick-up Voltage VDC max. <sup>1)</sup>	Drop-out Voltage VDC min. <sup>1)</sup>	Max. Voltage VDC *2)	Coil Resistance Ω
9	6.3	0.9	10.8	58 x (1±10%)
12	8.4	1.2	14.4	103 x (1±10%)
18	12.6	1.8	21.6	230 x (1±10%)
24	16.8	2.4	28.8	410 x (1±10%)

Notes: 1)The data shown above are initial values.

 Maximum voltage refers to the maximum voltage which relay coil could endure in a short period of time.

### SAFETY APPROVAL RATINGS

UL/CUL	AgSnO₂	26A 277VAC at 75°C
		22A 277VAC at 85°C
		26A 277VAC at 75°C
VDE	AgSnO <sub>2</sub>	22A 277VAC at 85°C 31A 250VAC cosØ =0.8 0.1s:10s 33A 250VAC cosØ =0.8 0.1s:10s (477)

Notes: 1) All values unspecified are at room temperature.2) Only typical loads are listed above. Other load specifications can be available upon request.

2018 Rev. 1.00

ORDERING INFORMATION						
	HF161F-W	/	12	-H	Т	(XXX)
Туре						
Coil voltage	9, 12, 18, 24VE	DC				
Contact arrange	contact arrangement H: 1 Form A					
Contact matcria	ntact matcrial T: AgSnO <sub>2</sub>					
Special code <sup>3)</sup> XXX: Customer special requirement Nil: Standard						
<ul> <li>Notes: 1) Water cleaning or surface process is not suggested after the flux-proofed relays are assembled on PCB.</li> <li>2) Flux-proofed relays can not be used in the environment with pollutants like H<sub>2</sub>S, SO<sub>2</sub>, NO<sub>2</sub>, dust, etc.</li> <li>3) The customer special requirement express as special code after evaluating by Hongfa. e.g. (414) stands for product with coil terminal of 1.4X0.4; e.g. (477) stands for Contact gap: 1.8mm.</li> </ul>						

## OUTLINE DIMENSIONS, WIRING DIAGRAM AND PC BOARD LAYOUT





## OUTLINE DIMENSIONS, WIRING DIAGRAM AND PC BOARD LAYOUT

Unit: mm

### Wiring Diagram



- Remark: 1) In case of no tolerance shown in outline dimension: outline dimension  $\leq$  1mm, tolerance should be ±0.2mm; outline dimension >1mm and  $\leq$ 5mm, tolerance should be ±0.3mm; outline dimension >5mm, tolerance should be ±0.4mm.
  - 2) The tolerance without indicating for PCB layout is always  $\pm 0.1$ mm.

### CHARACTERISTIC CURVES



MAXIMUM SWITCHING POWER

Contact Voltage (V)





Contact Current (A) Test conditions:

at 75°C, 1.5s on 1.5s off.

### Disclaimer

The specification is for reference only. See to "Terminology and Guidelines" for more information. Specifications subject to change without notice. We could not evaluate all the performance and all the parameters for every possible application. Thus the user should be in a right position to choose the suitable product for their own application. If there is any query, please contact Hongfa for the technical service. However, it is the user's responsibility to determine which product should be used only.

© Xiamen Hongfa Electroacoustic Co., Ltd. All rights of Hongfa are reserved.